

**IMPORTANT NOTE:** Directly connect the H10/3 BLACK/WHITE wire to the "GROUND" when this wire is not used.

|                                                                                                                                                                                                                    |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| 1. White / Black Wire: (-) Negative Safety Shut Down Input for Hood Pin Switch                                                                                                                                     |
| 2. White / Violet Wire: (+) Positive Safety Shut Down Input for Brake Switch                                                                                                                                       |
| 3. Black / White Wire: (-) Neutral Safety Switch Input &<br>(-) Remote Start Toggle Switch Input                                                                                                                   |
| 4. Blue Wire: Zone 2 / Instant Trigger Ground Input.                                                                                                                                                               |
| 5. White / Green Wire: (-) Diesel Wait-To-Start Input.                                                                                                                                                             |
| 6. Green Wire: Zone 3 / Negative Door Pin Trigger Input.                                                                                                                                                           |
| 7. Violet Wire: Zone 3 / Positive Door Pin Trigger Input.                                                                                                                                                          |
| 8. White / Blue Wire: (-) Instant Start and Turn Off Input.                                                                                                                                                        |
| 9. White / Red Wire: Tachometer Signal Input.                                                                                                                                                                      |
| 10. Blue / Black Wire: (-) 200mA Accessory 2 Output                                                                                                                                                                |
| 11. Yellow Wire: (-) 200mA Ignition 3 Control Output                                                                                                                                                               |
| 12. White Wire: (-) 200mA Dome Light Control Output                                                                                                                                                                |
| 13. Brown / White Wire: (-) 200mA Programmable Output<br>1. Horn Output (Factory Default Setting) or<br>2. Factory Security Rearm Signal Output                                                                    |
| 14. Pink Wire: (-) 200mA Programmable Output<br>1. 2 Steps Door Unlock Output (Factory Default Setting) or<br>2. Factory Security Disarm Signal Output or<br>3. Start Status (Shock Sensor By-Pass Control) Output |
| 15. Gray Wire: (-) 200mA Channel 3 (Trunk) Output                                                                                                                                                                  |
| 16. Black / Green Wire: (-) 200mA Channel 4 Programmable Output                                                                                                                                                    |
| 17. Black / Red Wire: (-) 200mA Channel 5 Programmable Output                                                                                                                                                      |
| 18. Black / Violet Wire: (-) 200mA Channel 6 Programmable Output                                                                                                                                                   |
| 19. Orange / White Wire: (-) 200mA Grounded Output When Disarmed                                                                                                                                                   |
| 20. Orange Wire: (-) 500mA Grounded Output When Armed                                                                                                                                                              |